

Saba Lighting Accessories

FEATURES

FEATURES

- Long life recyclable Lithium battery
- Integration of test switch and charge indicator
- Used for ANY exterior or interior luminaire
- Self-test function available.

Saba Lighting emergency drivers are UL Listed for (**factory or field installation**), unrivaled emergency solutions for LED productS with external driver. It allows the same LED luminaire to be used for normal and emergency operation and works in conjunction with an AC LED driver that converts new or existing LED fixtures into emergency lighting. It incorporates a long-life recyclable Lithium battery and is backed by a 5-Year Warranty.

When AC power fails, the emergency LED driver immediately switches to the emergency mode, operating the LEDs at a reduced lumen output for a minimum of 90 minutes. When AC power is restored, the emergency driver automatically returns to the charging mode.

SPECIFICATIONS

Model No.	BATT-BU(X)	
Output Power	16W	25W
Output Voltage	15V-54V	18V-54V
Input Current	50 mA (Max)	60 mA (Max)
Input Power	6 Watts (Max)	8 Watts (Max)
Input Voltage	100-277VAC, 50-60Hz	100-277VAC, 50-60Hz
Emergency Operation	≥90 Minutes	≥90 Minutes
Operating Temp	0° to 50° C	0° to 50° C
Output Class	UL LELV (Output protection self-resetting)	UL LELV (Output protection self-resetting)
Battery	Lithium	Lithium
Recharge	36 Hrs	36 Hrs
Dimensions / Weight	L 17.14" x W 2.13" x H 1.38"	
SKU	BATT-BU16-SF	BATT-BU25-SF

INSTALLATION DIAGRAM

